



## Steps to use the Firmware 3.6

1. do a Firmware upgrade to FlipBox
2. Connect the FlipBox to the computer
3. Start the TS ConfigTOOL application



4. Chose **File naming** tab



5. You can select one from predefined templates or You can create your own template

As You can see there are two filename templates: first for card download and the second for tachograph download. You can use maximum 16 characters to define your template. Characters *t, d, c, v, r, f, s, n, i* will be replaced with corresponding data; any other filename compatible character will be included into filename.


#### Examples:

CARD\_c\_n\_d\_t.C1B  
=> CARD\_HU\_\_12345678912345\_100624\_1053.C1B

c\_d\_t\_n\_s\_f.C2B  
=> RO\_100624\_1053\_12345678912345\_Robert\_Smith.C2B

ROBERT\_c\_dt.ABC  
=> ROBERT\_FR\_1006241053.ABC

#### Test result:



Name	Ext	Size	Date
[..]	<DIR>	06/	
FIN10000000000035_Krista_4_N_idis_4_1006240838	DDD	21,679	06/
FIN10000000000035_Krista_4_N_idis_4_1006240857	DDD	21,679	06/
CARD_FIN_10000000000035_100624_1137	C1B	21,679	06/
FIN_100624_1141_10000000000035_N_idis_4_Krista_4_	C2B	21,679	06/
ROBERT_FIN_1006241143	ABC	21,679	06/

For card download naming You can use *t, d, c, f, s, n, i* as replaceable config characters

For tachograph download naming You can use *t, d, c, v, r* as replaceable config characters